

KEYED NOTES	
E11	BEC SHALL INSTALL OWNER-FURNISHED CORD REEL FOR DISPLAY POWER DROPS. SEE SPEC SECTION 26 05 33.2.10 A FOR MORE DETAILS.
E11A	BEC TO PROVIDE ABOVE CEILING JUNCTION BOX AND CORD DROP AS SHOWN IN ACCESSIBLE LOCATION ON DETAIL ESD-16 ON E5-SERIES DRAWINGS. CORD DROP TO BE WHITE IN AREAS IN VIEW TO CUSTOMERS. FINAL DROP TO BE INSTALLED ONLY AFTER CASE HAS BEEN SET. MATCH "50" CABLE SIZE AND RECEPTACLE WITH CASE REQUIREMENTS IN FIELD. PRIOR TO INSTALLATION VERIFY FINAL LOCATION WITH KROGER PM.
E40A	FLUSH MOUNT ALL WALL OUTLETS IN FOOD PREP AREAS. PROVIDE GROUND FAULT CIRCUIT INTERRUPTER PROTECTION FOR ALL 120V AND 208V SINGLE-PHASE 50 AMP RECEPTACLES OR LESS, AND 208V THREE-PHASE 100 AMP RECEPTACLES OR LESS, INSTALLED IN KITCHEN/FOOD PREP AREAS. MOUNT HORIZONTALLY. IN ADDITION TO THE ABOVE, PROVIDE WEATHERPROOF COVERS (NEMA 3R WHILE IN USE) FOR ALL OUTLETS IN PRODUCE PREP AND MEAT PREP. NO ELECTRICAL CONDUIT SHALL BE INSTALLED EXPOSED IN PREP AREA INTERIORS. INSTALL ALL COUNTER-HEIGHT POWER & SYSTEM WALL OUTLETS HORIZONTALLY AT 48" A.F.F. CENTER THEM IN RESPECTIVE TILE OF THE BAND OF BULLNOSE WALL TILE THAT WILL BE INSTALLED AT THIS HEIGHT. SEE ARCHITECTURAL DETAILS AND FIELD COORDINATE WITH TILE INSTALLER. DO NOT INSTALL POWER OR SYSTEMS OUTLETS WHERE WALL FINISH STYLES MEET - EITHER INSTALL FULLY IN BELOW THE BAND OF BULLNOSE TILE OR IN BULLNOSE WALL TILE AS DESCRIBED ABOVE.


KEYED NOTES	
E42	BEC SHALL PROVIDE JUNCTION BOX, CONDUIT, AND WIRE FOR PLUGMOLD. FEC SHALL PROVIDE PLUGMOLD (WIREMOLD #2000 SERIES, 2-CIRCUIT, WITH "QF" SERIES SINGLE RECEPTACLES ON "F" CENTERS). BEC TO INSTALL RECESSED SINGLE GANG WALL BOX TURNED HORIZONTALLY. USE SINGLE GANG W/48" ADAPTER BOX FOR CONNECTION TO PLUGMOLD. COORDINATE WITH FEC. PAINT PLUGMOLD TO MATCH WALL. PROVIDE PLUGMOLD TO BE A LENGTH OF ASSOCIATED FURNITURE.
E43	FEC SHALL PROVIDE DUPLEX CONVENIENCE RECEPTACLE ON BASE OR TOP OF CASE. FIELD VERIFY EXACT LOCATION.
E44	BEC SHALL PROVIDE WIRING HOME-RUN FOR EQUIPMENT INDICATED FROM JUNCTION BOX BENEATH ADJACENT CASES. FEC SHALL EXTEND WIRING AND RACEWAY FROM THOSE JUNCTION BOXES TO EQUIPMENT SERVED AS REQUIRED.
E47A	BEC TO PROVIDE JUNCTION BOX AND CORD DROP AS SHOWN ON DETAIL 16A ON E5-SERIES DRAWINGS. CORD DROP TO BE WHITE IN AREAS IN VIEW TO CUSTOMERS AND BLACK IN ROOMS NOT SUBJECT TO VIEW BY CUSTOMERS. FEC SHALL MAKE FINAL CONNECTIONS TO ISLAND EQUIPMENT AS SHOWN ON THE POWER PLANS.
RE1	RECONNECT CIRCUIT TO RELOCATED OR NEW REPLACEMENT REFRIGERATION EQUIPMENT. UTILIZE EXISTING CONDUIT, RACEWAY, JUNCTION BOXES, WIRING, CIRCUITING, ETC. WHEREVER POSSIBLE. CONNECT FANS TO CIRCUITS THAT PREVIOUSLY SERVED FANS, LIGHTS TO CIRCUITS THAT PREVIOUSLY SERVED LIGHTS, ETC. PROVIDE ADDITIONAL CONDUIT AND WIRING AS IF REQUIRED.
RE2	RELOCATE EXISTING EQUIPMENT TO LOCATION SHOWN. SEE DEMO POWER PLAN FOR EXISTING LOCATION. EXTEND/MODIFY/SUPPLEMENT EXISTING CONDUIT AND WIRE FROM PREVIOUS CIRCUIT LOCATION TO NEW. PROVIDE ALL MATERIALS AS REQUIRED FOR A COMPLETE RELOCATION.
RE3	EXTEND/SUPPLEMENT EXISTING CIRCUIT(S) TO NEW EQUIPMENT SHOWN. CONNECT FANS TO CIRCUITS THAT PREVIOUSLY SERVED FANS, LIGHTS TO CIRCUITS THAT PREVIOUSLY SERVED LIGHTS, ETC. E.C. TO ENSURE NEWLY METERED LOAD OF EACH CIRCUIT DOES NOT EXCEED 1800W. PROVIDE ADDITIONAL CIRCUITS FROM SIMILAR PANEL FOR LOADS THAT EXCEED THIS LIMIT.
RE4	ELECTRICAL CONTRACTOR TO DISCONNECT AND RECONNECT EQUIPMENT AT INDICATED AREAS FOR COUNTER REPLACEMENT. COORDINATE WITH GENERAL CONTRACTOR FOR SCHEDULE AND SCOPE.
RE5	ELECTRICAL CONTRACTOR TO CONNECT NEW SIGNAGE TO EXISTING CIRCUIT MADE AVAILABLE THROUGH DEMOLITION OF EXISTING SIGNAGE. EXTEND/MODIFY/SUPPLEMENT EXISTING CONDUIT AND WIRE TO NEW LOCATION AS NEEDED. PROVIDE ALL MATERIAL AS REQUIRED FOR A COMPLETE INSTALLATION. COORDINATE EXACT LOCATION AND ELECTRICAL REQUIREMENTS WITH KROGER PM PRIOR TO ROUGH-IN.

SPARE CIRCUITS AND TV MONITOR RECEPTACLES

- A. IN ADDITION TO ITEM(S) BELOW AND IN ADDITION TO ALL OTHER ELECTRICAL WORK SHOWN ON DRAWINGS, PROVIDE A TOTAL OF FIVE (5) SPARE BRANCH CIRCUITS (INCLUDING NEW 1" CONDUIT PER CIRCUIT AND LABOR TO INSTALL CONDUIT, WIRE, AND TO MAKE FINAL CONNECTION). EACH UP TO 100 FEET FROM THE RESPECTIVE SOURCE PANELBOARD FOR FUTURE USE OR ADDITIONAL WORK AS DIRECTED BY KROGER. ASSUME EACH CIRCUIT SHALL BE 120V/20A/1P, BUT FIELD VERIFY EACH.
- B. IN ADDITION TO ALL OTHER ELECTRICAL WORK SHOWN ON DRAWINGS, PROVIDE ONE (1) DUPLEX RECEPTACLE EACH, FOR UP TO FOUR (4) TELEVISION MONITORS THAT WILL BE INSTALLED AT VARIOUS LOCATIONS THROUGHOUT THE FACILITY AS REQUIRED. PROVIDE 20A/120V BRANCH CIRCUIT CONDUIT, WIRING AND HOME-RUNS TO NEAREST NORMAL GENERAL POWER PANELBOARD THAT HAS AVAILABLE POLE SPACE & BREAKERS. UP TO FOUR (4) MONITORS MAY BE CONNECTED TO THE SAME CIRCUIT. DETERMINE EXACT LOCATIONS IN FIELD.


GENERAL POWER NOTES

- A. REFER TO EQUIPMENT SCHEDULES ON SHEET E6.2 FOR MOUNTING HEIGHTS AND ADDITIONAL INFORMATION. SEE DETAILS ON E5-SERIES DRAWINGS WHERE APPLICABLE.
- B. ALL CONDUITS FOR COOLERS, FREEZERS, PREP ROOM EQUIPMENT FED FROM ABOVE SHALL BE RUN ON TOP OF INSULATED ROOF PANEL AND STUBBED THRU PANEL INTO PREP ROOM AT EQUIPMENT LOCATION(S) SHOWN. SEE ESD-26 ON E5-SERIES DRAWINGS.
- C. FIELD COORDINATE UNDER-SLAB CONDUIT AND RACEWAY LAYOUTS WITH ALL AFFECTED PARTIES PRIOR TO SLAB PLACEMENT.
- D. PROVIDE 10 FEET OF FLEXIBLE CONDUIT FOR REFRIGERATED CASES SERVED FROM WALL JUNCTION BOXES FOR CONNECTION TO CASES BY THE FUTURE ELECTRICAL CONTRACTOR.
- E. REFER TO ELECTRICAL DIMENSION PLANS FOR GENERAL DIMENSIONAL INFORMATION THAT SHALL ALSO SCHEMATICALLY APPLY FOR CORRESPONDING SYSTEMS WORK.
- F. CIRCUITS PULLED THRU RACEWAYS SHALL BE 120V UNLESS INDICATED OTHERWISE.
- G. WHERE MORE THAN (1) ELECTRICAL LOAD IS INDICATED AT AN OUTLET, PROVIDE A SEPARATE CIRCUIT FROM THE ELECTRICAL PANEL FOR EACH LOAD.
- H. ALL ELECTRICAL AND COMMUNICATION JUNCTION/OUTLET BOXES SHOWN AGAINST THE WALL SHALL BE MOUNTED IN THE WALL. REFER TO THE ELECTRICAL EQUIPMENT SCHEDULE FOR MOUNTING INFORMATION.
- I. IN GENERAL, RECEPTACLES SHOWN WITHOUT EQUIPMENT MARKING OR OTHER CALLOUT ARE CONVENIENCE OUTLETS THAT SHALL BE MOUNTED AT 18" A.F.F.
- J. REGARDLESS OF WHERE JB'S ARE SHOWN ON DRAWINGS, FEED CASES FROM WALL WHEREVER CASES ARE LOCATED AGAINST A WALL. INSTALL WALL OUTLET/JUNCTION BOXES FOR SUCH CASES SO THAT BOTTOMS OF BOXES ARE TWO (2) INCHES ABOVE TOP OF RESPECTIVE CASE (FIELD VERIFY).
- K. SEE DETAIL "F" ON E5-SERIES DRAWINGS FOR SPECIAL CIRCUITING AND DIMENSIONING REQUIREMENTS THAT APPLY TO REFRIGERATED CASE EQUIPMENT.
- L. FEC IS RESPONSIBLE FOR ALL NEC REQUIRED LOCAL DISCONNECTING MEANS (NOT FURNISHED WITH EQUIPMENT OR BY KROGER) FOR A COMPLETE INSTALLATION. PROVIDE ALL DISCONNECTING MEANS PER NEC 422.31.



2 ELECTRICAL POWER PLAN AND DETAILS - OFFICE MEZZ.
3/32" = 1'-0"

1 ELECTRICAL POWER PLAN AND DETAILS
3/32" = 1'-0"



OWNERSHIP OF INSTRUMENTS OF SERVICE

All reports, plans, specifications, computer files, field data, notes and other documents and instruments prepared by the Consultant as instruments of service shall remain the property of the Consultant. The Consultant shall retain all common law, statutory and other reserved rights, including, without limitation, the copyright therein.

Date Change Description

KROGER N641



2028 E HARBOR RD

PORT CLINTON, OH 43452

for

THE KROGER COMPANY



300 Spruce Street

Suite 300

Columbus, Ohio 43215

Phone: (614) 461-4664

Fax: (614) 290-8881

www.moody-nolan.com

Dwg. Coord.: CJC

Tech. Coord.: JAT

Proj. # 25835.00

ELECTRICAL POWER PLAN
AND DETAILS

E1.3

BID/PERMIT

12/13/2023