

## SECTION 26 24 16 - PANELBOARDS

### PART 1 - GENERAL

#### 1.1 SUMMARY

A. Section includes:

1. **KROGER DIRECT BUY PROGRAM:** Owner supplied/Contractor installed.
  - a. The Kroger Company will supply distribution panelboards and lighting and appliance branch-circuit panelboards indicated on drawings for:
    - 1) Power Distribution Panelboards
    - 2) Lighting and Appliance Panelboards
  - b. Comply with requirements in Division 00 Section "General Conditions."
2. Contractor supplied items:
  - a. Branch-circuit breakers for existing panelboards unless branch-circuit breaker is noted on drawings as existing to remain.
  - b. Accessories as required for a complete installation.
3. Contractor installed items:
  - a. Distribution panelboards and lighting and appliance branch-circuit panelboards.
  - b. Branch-circuit breakers for existing panelboards unless branch-circuit breaker is noted on drawings as existing to remain.
4. Panels, accessories and installation as required for a complete system.
5. Equipment does not have to match existing equipment.

#### 1.2 SUBMITTALS

- A. The Owner will provide the following submittals for the Contractor's review. The Contractor shall review and return submittals as specified in Division 00 Section "General Conditions."
1. Product Data: For each type of panelboard, overcurrent protective device, accessory, and component indicated. Include dimensions and manufacturers' technical data on features, performance, electrical characteristics, ratings, and finishes.
  2. Shop Drawings: For each panelboard and related equipment.

### 1.3 QUALITY ASSURANCE

- A. Electrical Components, Devices, and Accessories: Listed and labeled as defined in NFPA 70, Article 100, by a testing agency acceptable to authorities having jurisdiction, and marked for intended use.
- B. Comply with NEMA PB 1.
- C. Comply with NFPA 70.

## PART 2 - PRODUCTS

### 2.1 PANELBOARDS

- A. Refer to Division 01 Section "Vendor Contact List" for information on panelboards.

## PART 3 - EXECUTION

### 3.1 INSTALLATION

- A. Install panelboards and accessories according to NEMA PB 1.1.
- B. Mount top of trim **74 inches (1880 mm)** above finished floor, unless otherwise indicated.
- C. Mount plumb and rigid without distortion of box. Mount recessed panelboards with fronts uniformly flush with wall finish.
- D. Install overcurrent protective devices and controllers.
  - 1. Set field-adjustable switches and circuit-breaker trip ranges.
- E. Install filler plates in unused spaces.
- F. Stub four **1-inch (27-GRC)** empty conduits from panelboard into accessible ceiling space or space designated to be ceiling space in the future. Stub four **1-inch (27-GRC)** empty conduits into raised floor space or below slab not on grade.
- G. Identify field-installed conductors, interconnecting wiring, and components; provide warning signs as specified in Division 26 Section "Identification for Electrical Systems."
- H. Ground equipment according to Division 26 Section "Grounding and Bonding for Electrical Systems."
- I. Connect wiring according to Division 26 Section "Low Voltage Electrical Power Conductors and Cables."

3.2 FIELD QUALITY CONTROL

A. Prepare for acceptance tests as follows:

1. Test insulation resistance for each panelboard bus, component, connecting supply, feeder, and control circuit.
2. Test continuity of each circuit.

B. Perform the following field tests and inspections and prepare test reports:

1. Perform each electrical test and visual and mechanical inspection stated in NETA ATS, Section 7.5 for switches and Section 7.6 for molded-case circuit breakers. Certify compliance with test parameters.
2. Correct malfunctioning units on-site, where possible, and retest to demonstrate compliance; otherwise, replace with new units and retest.
3. Set field adjustable circuit breaker “trip” ratings in compliance with manufacturer’s recommendations.

END OF SECTION 26 24 16

**BLANK SHEET**